



Typ E-2800  
E-3000

### NÄTAGGREGAT TYP E-2800

Nättaggregat speciellt konstruerat för kondensatormikrofon typ 8-CK och C-8. Kondensatormikrofon typ C-2, se blad E-4, kan även anslutas till detta nättaggregat.

### NÄTAGGREGAT TYP E-3000

Nättaggregat speciellt konstruerat för kondensatormikrofon typ C-2, se blad E-4.

#### TEKNISKA DATA:

Anodspänning för i mikrofonen inbyggd förstärkare	120 volt
Polarisationsspänning för mikrofonkapsel	120 volt
Spänningstabilisatorrör	OB2
Glödspänning	4 volt
Glödström	0,1 amp

#### KONTAKTER

För typ E-2800:

6-polig chassikontakt för anslutning till mikrofonen	Typ: 6-14
3-polig chassikontakt för anslutning till förstärkaren	Typ: 3-14

För typ E-3000:

5-polig chassikontakt för anslutning till mikrofonen	Typ: 5-14
3-polig chassikontakt för anslutning till förstärkaren	Typ: 3-14

#### DIMENSIONER

Längd	150 mm
Bredd	100 mm
Höjd	75 mm
Vikt	1,8 kg

### STEREO NÄTAGGREGAT TYP E-3100

Detta nättaggregat är speciellt konstruerat för STEREO-mikrofon typ ST-5; utförliga data se blad E-5.

#### TEKNISKA DATA:

Anodspänning till förstärkarna i STEREO-mikrofonen	120 volt
Polarisationsspänning för mikrofonkapselarna	120 volt
Stabilisatorrör	OB2
Glödspänning	2x4 volt
Glödström	2x0,1 amp

#### KONTAKTER

12-polig chassikontakt för anslutning till mikrofon	165-12
5-polig chassikontakt för mikrofonanslutning till förstärkarna	5-14

#### UTFÖRANDE:

Kraftig kåpa av 1 mm plåt.  
Ytbehandling: Brännlackerad i 2 grå färgnyanser.  
2-polig vippströmbrytare.  
1,5 m nätsladd med kontakt för anslutning till växelström.

### POWER SUPPLY TYPE E-2800

The power supply unit is particularly constructed for condenser microphone type 8-CK and C-8. The condenser microphone type C-2, see page E-4, may also be connected to this unit.

### POWER SUPPLY TYPE E-3000

This power supply unit is particularly constructed for condenser microphone type C-2, see page E-4.

#### TECHNICAL DATA:

Anode voltage for in the microphone built in amplifier	120 V
Polarization voltage for the microphone cartridge	120 V
Voltage reg. tube	OB2
Heater voltage	4 V
Heater current	0,1 Amp

#### CONNECTORS

For type E-2800:

6 pole chassis con. for connection to the microphone	type 6-14
3 pole chassis con. for connection to the amplifier	type 3-14

For type E-3000:

5 pole chassis con. for connection to the microphone	type 5-14
3 pole chassis con. for connection to the amplifier	type 3-14

#### SIZE

Length	150 mm
Width	100 mm
Height	75 mm
Weight	1,8 kgs

### STEREO POWER SUPPLY TYPE E-3100

This power supply unit is particularly constructed for STEREO microphone type ST-5; detailed specifications see page E-5.

#### TECHNICAL DATA:

Anode voltage to the amplifiers in the STEREO microphone	120 V
Polarization voltage for the microphone cartridges	120 V
Voltage reg. tube	OB2
Heater voltage	2x4 V
Heater current	2x0,1 Amps

#### CONNECTORS

12 pole chassis con. for microphone	120 V 165-12
5 pole chassis con. for microphone connection to the amplifiers	5-14

#### CONSTRUCTION:

Case: 1 mm plate.  
Finish: furnace varnished in 2 gray shades.  
2 pole toggle switch.  
1,5 mtrs line cable for connection to alternating current.



Typ E-3100